

2622002 / EXXACT 15min-8h timer

Exxact electronic timer 1-pole white The timer can be used as a fire alarm disconnection device. The desired disconnection time between 15min. and 8h is set in the device during the installation phase.

- Adjustable delay: 5, 30 min, 1, 2, 4 or 8 hours
- Requires a neutral conductor
- Red LED indication when the timer is active

SKU	7044413
Product series	EXXACT

**Technical data**

Operating voltage (VAC)	230
Installation	does not contain frames
Width (mm)	80
Height (mm)	55
Length (Depth) (mm)	80
Net weight (kg)	0.085
Colour	White

We withhold the right to make changes

Hedengren Security Oy Ab
www.hedengren.com
tel. +358 (0) 207 638 001
security@hedengren.fi
PP.KK.VVV