

## VAR-KOJE / Warning device

- Volume 78 dB / frequency 2.3 kHz
- A red flashing LED indicator and an intermittent tone

SKU

8000115



## Technical data

	78 dB / 30 cm (2,3 kHz)
<b>Operating voltage (VDC)</b>	9,5 - 28 VAC / 9,5 - 35 VDC
<b>Operating current, normal (mA)</b>	60.2
<b>Operating temperature</b>	5 - 40 °C
<b>Mounting method</b>	Recessed/flush mount

<b>Installation</b>	Flush mounting
<b>Width (mm)</b>	71
<b>Height (mm)</b>	71
<b>Length (Depth) (mm)</b>	46
<b>Net weight (kg)</b>	0.05



We withhold the right to make changes

Hedengren Security Oy Ab  
www.hedengren.com  
tel. +358 (0) 207 638 001  
security@hedengren.fi  
23.11.2024