

**VAR-KOJE / Warning device**

- Volume 78 dB / frequency 2.3 kHz
- A red flashing LED indicator and an intermittent tone

SKU

8000115

**Technical data**

|                                |                             |
|--------------------------------|-----------------------------|
|                                | 78 dB / 30 cm (2,3 kHz)     |
| Operating voltage (VDC)        | 9,5 - 28 VAC / 9,5 - 35 VDC |
| Operating current, normal (mA) | 60.2                        |
| Operating temperature          | 5 - 40 °C                   |
| Mounting method                | Recessed/flush mount        |

|                     |                |
|---------------------|----------------|
| Installation        | Flush mounting |
| Width (mm)          | 71             |
| Height (mm)         | 71             |
| Length (Depth) (mm) | 46             |
| Net weight (kg)     | 0.05           |



We withhold the right to make changes

Hedengren Security Oy Ab  
www.hedengren.com  
tel. +358 (0) 207 638 001  
security@hedengren.fi  
13.05.2024