

FLASHNI-24V / Conventional sounder beacon

A conventional sounder beacon to be installed in the bell line.

- Combined siren and beacon
- 1 W/60 flashes per minute

SKU	8000198
Product series	Firescape



Technical data

Operating voltage (VDC)	2
Operating current, normal (mA)	68
Width (mm)	93
Height (mm)	121
Length (Depth) (mm)	0
Net weight (kg)	0.375
Colour	Red



We withhold the right to make changes

Hedengren Security Oy Ab
www.hedengren.com
tel. +358 (0) 207 638 001
security@hedengren.fi
PP.KK.VVV